

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 1 263 155 A1

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
04.12.2002 Bulletin 2002/49

(51) Int Cl.7: **H04B 10/18**(21) Application number: **01304727.9**(22) Date of filing: **29.05.2001**

(84) Designated Contracting States:

**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE TR**

Designated Extension States:

AL LT LV MK RO SI

(71) Applicant: **Aston Photonic Technologies Ltd.**
Birmingham B7 4BB (GB)

(72) Inventors:

- **Turitsyn, Sergei Konstantinovich**
Birmingham B4 7ET (GB)

• **Bennion, Ian**

Birmingham B4 7ET (GB)

(74) Representative: **Finnie, Peter John**
Gill Jennings & Every,
Broadgate House,
7 Eldon Street
London EC2M 7LH (GB)

(54) **Chromatic dispersion compensation in an optical transmission system**

(57) An optical pulse transmission line portion 10, having dispersion slope compensation, comprising an optical waveguide 12 (length L_1 , dispersion parameter D_1) having a dispersion slope parameter (S_1) of a first sign, and dispersion compensation means 14 (length L_2 , dispersion parameter D_2) having a dispersion slope parameter (S_2) of the opposite sign. The path average dispersion ($\langle D \rangle$) of the transmission line portion being:

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

Optical pulse transmission line portion components and an optical pulse transmission line having dispersion slope compensation are also provided. A further aspect of the invention provides an optical pulse transmission line element, having dispersion compensation and dispersion slope compensation, comprising an optical waveguide (length L_1 , dispersion parameter D_1 , dispersion slope parameter S_1) and first and second dispersion compensation means (lengths L_2, L_3 , dispersion parameters D_2, D_3 , dispersion slope parameters S_2, S_3). The path average dispersion ($\langle D \rangle$) of the transmission line element (total length L) being:

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2}$$

Optical pulse transmission line element components and an optical pulse transmission line having dispersion compensation and dispersion slope compensation are also provided by the invention.

EP 1 263 155 A1




FIG. 1

Description

[0001] The invention relates to optical pulse transmission line parts which are particularly, but not exclusively, for use in high capacity, wavelength division multiplexed (WDM) optical waveguide transmission lines employing return-to-zero (RZ) optical pulses. The invention also relates to components for parts of an optical pulse transmission line, and to an optical pulse transmission line.

[0002] At high bit rates optical communication systems suffer degradation of their transmission capacity. This is mainly due to the detrimental effects on the optical pulses of chromatic dispersion, fibre non-linearity and noise from optical amplifiers in the system.

[0003] In the transmission of soliton pulses, positive use is made of the fibre non-linearity by achieving a balance with the pulse broadening due to dispersion in the region of the anomalous chromatic dispersion. Conventional soliton transmission lines comprise optical fibre which has a constant, or slightly varying, dispersion coefficient. However, the distance over which soliton pulses may be transmitted along such a transmission line is limited by two contradicting requirements: the dispersion must be low in order to minimise Gordon-Haus timing jitter, which is driven by optical amplifier noise; and the dispersion must be high in order to suppress four-wave mixing in wavelength division multiplexed transmission systems. This contradiction is resolved by using a technique known as dispersion management in which the optical fibre transmission line has high local dispersion and low path-average dispersion.

[0004] One of the major factors limiting optical data transmission distance and capacity in WDM systems is the effect of dispersion slope, which is a wavelength dependent parameter. The dispersion slope of an optical waveguide causes a variation in the dispersion parameters of the waveguide as a result of a change in the wavelength of an optical signal propagating along the waveguide. That is to say, the dispersion experienced by an optical signal propagating along the waveguide is dependent upon the wavelength of the optical signal. Therefore each optical channel in a WDM system will experience a different dispersion parameter. As a result it is difficult to achieve system optimisation for all wavelength channels simultaneously.

[0005] Existing approaches to compensating for the effect of dispersion slope are rather complex. These include per channel dispersion slope compensation, the manufacture of pairs of optical fibres having opposite values of dispersion and dispersion slope, and the manufacture of compensating optical fibres capable of compensating for both the dispersion and dispersion slope of known transmission fibres, such as standard monomode fibre (SMF).

[0006] According to a first aspect of the present invention there is provided an optical pulse transmission line portion having dispersion slope compensation, the transmission line portion comprising:

a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign,
optically coupled to
first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign,

wherein the path average dispersion slope of the transmission line portion is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2$$

and the path average dispersion ($\langle D \rangle$) of the transmission line portion is generally non zero, and is given by

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

[0007] The path average dispersion of the transmission line portion is preferably wavelength independent.

[0008] The optical pulse transmission line portion is preferably for inclusion in a wavelength division multiplexed optical pulse transmission system.

[0009] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton. The optical pulse may alternatively be a chirped return-to-zero optical signal.

[0010] The first optical waveguide and the first dispersion slope compensating means are desirably arranged in a precompensating dispersion map configuration, or may alternatively be arranged in a postcompensating dispersion map configuration.

[0011] The transmission line portion preferably further comprises an optical amplifier. The optical amplifier may be optically coupled to the dispersion map at one end of the dispersion map or at a location along the dispersion map.

[0012] The transmission line portion may further comprise a second optical waveguide of a third length (L_3) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign and a second dispersion slope compensating means of a fourth length (L_4) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign.

[0013] The first and second optical waveguides and the first and second dispersion slope compensating means are desirably optically coupled together in a symmetric dispersion map configuration. The transmission line portion may further comprise a second optical amplifier. Desirably, one of the first and second optical amplifiers is provided at an end of the dispersion map and the other of the first and second optical amplifiers is provided towards the middle of the dispersion map.

[0014] The or each optical amplifier may be a fibre amplifier, such as an erbium doped fibre amplifier, or a fibre Raman amplifier. The or each optical amplifier may alternatively be a semiconductor optical amplifier device.

[0015] The first and second optical waveguides are preferably sections of a first optical fibre. The first optical fibre may be a transmission fibre such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.

[0016] The first and second dispersion slope compensating means preferably comprise sections of a third optical waveguide, which is most preferably a second optical fibre. The second optical fibre may be a compensating fibre, such as dispersion compensating fibre or reverse dispersion fibre.

[0017] The first and second dispersion slope compensating means may alternatively or additionally comprise sections of a fourth optical waveguide including an optical grating. The fourth optical waveguide is preferably a third optical fibre. The optical grating is preferably an optical fibre grating, such as a fibre Bragg grating.

[0018] According to a second aspect of the present invention there is provided optical pulse transmission line portion components for incorporation into an existing terrestrial communication line which comprises a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign, the components comprising:

first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign, the first dispersion slope compensating means being connectable in optical communication with the first optical waveguide to form therewith an optical pulse transmission line portion having compensated dispersion slope,

wherein the path average dispersion slope of the transmission line portion is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2$$

and the path average dispersion ($\langle D \rangle$) of the transmission line portion is generally non zero, and is given by

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

[0019] The path average dispersion of the transmission line portion is preferably wavelength independent.

[0020] The optical pulse transmission line portion preferably forms part of a wavelength division multiplexed optical pulse transmission system.

[0021] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton.

The optical pulse may alternatively be a chirped return-to-zero signal.

[0022] Desirably the first optical waveguide and the first dispersion slope compensating means, when connected together, form a precompensating dispersion map, or may alternatively form a postcompensating dispersion map.

[0023] The transmission line portion components preferably further comprise a first optical amplifier, being connectable in optical communication with the optical pulse transmission line portion. The first optical amplifier may be connected in optical communication with the transmission line portion at one end of the dispersion map or at a location along the dispersion map.

[0024] The existing terrestrial communication line may further comprise a second optical waveguide of a third length (L_3) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign.

[0025] The first and second optical waveguides are preferably sections of a first optical fibre. The first optical fibre may be a transmission fibre such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.

[0026] The transmission line portion components may further comprise a second dispersion slope compensating means of a fourth length (L_4) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign, and being connectable in optical communication with one or more of the aforementioned components,

and the first and second optical waveguides.

[0027] Desirably, the first and second optical waveguides and the first and second dispersion slope compensating means, when optically coupled together, form a symmetric dispersion map. The transmission line portion components may further comprise a second optical amplifier connectable in optical communication with one or more of the aforementioned components, and the first and second optical waveguides. Desirably, one of the first and second optical amplifiers is provided at an end of the dispersion map and the other of the first and second optical amplifiers is provided towards the middle of the dispersion map.

[0028] The or each optical amplifier may be a fibre amplifier, such as an erbium doped fibre amplifier, or a fibre Raman amplifier. The or each optical amplifier may alternatively be a semiconductor optical amplifier device.

[0029] The first and second dispersion slope compensating means preferably comprise sections of a third optical waveguide, which is most preferably a second optical fibre. The second optical fibre may be a compensating fibre, such as dispersion compensating fibre or reverse dispersion fibre.

[0030] The first and second dispersion slope compensating means may alternatively or additionally comprise sections of a fourth optical waveguide including an optical grating. The fourth optical waveguide is preferably third optical fibre. The optical grating is preferably an optical fibre grating, such as a fibre Bragg grating.

[0031] According to a third aspect of the present invention there is provided an optical pulse transmission line having dispersion slope compensation, the optical pulse transmission line comprising a plurality of optical pulse transmission line portions, according to any of paragraphs 6 to 17 above, connected in optical communication in series.

[0032] The optical pulse transmission line is preferably for inclusion in a wavelength division multiplexed optical pulse transmission system.

[0033] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton. The optical pulse may alternatively be a chirped return-to-zero signal.

[0034] According to a fourth aspect of the present invention there is provided an optical pulse transmission line element having dispersion compensation and dispersion slope compensation, the transmission line element comprising:

a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a first dispersion slope parameter (S_1),
 first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a second dispersion slope parameter (S_2), and
 second dispersion slope compensating means of a third length (L_3) having a third dispersion parameter (D_3) and a third dispersion slope parameter (S_3),
 the first optical waveguide, the first dispersion slope compensating means and the second dispersion slope compensating means being connected together in optical communication to form the transmission line element,

wherein the path average dispersion slope of the transmission line element is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2 + S_3 L_3$$

and the path average dispersion ($\langle D \rangle$) of the transmission line element, having a total length $L = L_1 + L_2 + L_3$ is given by

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2}$$

[0035] The path average dispersion of the transmission line element is preferably wavelength independent.

[0036] Preferably, $\pm [D_1 (S_3 - S_2) + (D_2 - D_3) S_1] \pm (S_3 - S_2)$ is greater than zero, whereby the path average dispersion may be controlled by selection of the length (L_1) of the first optical waveguide. The path average dispersion of the transmission line element is desirably substantially zero. The path average dispersion of the transmission line element may alternatively be non-zero.

[0037] The optical pulse transmission line element is preferably for inclusion in a wavelength division multiplexed optical pulse transmission system.

[0038] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton. The optical pulse may alternatively be a chirped return-to-zero signal.

[0039] The first optical waveguide is preferably a first optical fibre. The first optical fibre may be a transmission fibre, such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.

[0040] The first dispersion slope compensating means is preferably a second optical waveguide. The second optical waveguide is desirably a second optical fibre, which may be a compensating fibre such as reverse dispersion fibre or dispersion compensating fibre. The first dispersion slope compensating means may comprise two parts, each part comprising a section of the second optical fibre.

[0041] The second dispersion slope compensating means preferably comprise a third optical waveguide. The third optical waveguide is desirably a third optical fibre, which may be a compensating fibre such as dispersion compensating fibre or reverse dispersion fibre.

[0042] The second dispersion slope compensating means may alternatively or additionally comprise a fourth optical waveguide including an optical grating. The fourth optical waveguide is preferably a fourth optical fibre. The optical grating is preferably an optical fibre grating, such as a fibre Bragg grating.

[0043] The transmission line element desirably further comprises at least one optical amplifier.

[0044] Desirably, the transmission line element comprises a plurality of sections of the first optical waveguide.

[0045] A first section of the first optical waveguide and the first dispersion slope compensating means are preferably arranged to form an optical pulse transmission line portion according to the first aspect of the invention.

[0046] The transmission line element desirably comprises:

first and second sections of the first optical waveguide, first and second parts of the first dispersion slope compensating means and first and second optical amplifiers, all being arranged to form a first optical pulse transmission line portion according to the first aspect of the invention, having a symmetric dispersion map;

optically coupled in series to

a second optical pulse transmission line portion according to the first aspect of the invention comprising the second dispersion slope compensating means, a third section of the first optical waveguide, and a third optical amplifier.

[0047] The or each optical amplifier is preferably a fibre amplifier, such as an erbium doped fibre amplifier or a fibre Raman amplifier. The or each optical amplifier may alternatively be a semiconductor optical amplifier device.

[0048] Desirably, a plurality of first optical pulse transmission line portions according to the first aspect of the invention, having a symmetric dispersion map, are provided, connected together in series in optical communication.

[0049] The path average dispersion slope of the or each first optical pulse transmission line portion is desirably substantially zero. The path average dispersion of the or each first optical pulse transmission line portion is desirably non zero and of a first sign.

[0050] The path average dispersion slope of the second optical pulse transmission line portion is desirably substantially zero. The path average dispersion of the second optical pulse transmission line portion is desirably non zero and of the opposite sign.

[0051] The path average dispersion of the optical pulse transmission line element is preferably equal to the sum of the path average dispersion of the or each first optical pulse transmission line portion and the path average dispersion of the second optical pulse transmission line portion. The path average dispersion of the transmission line element is desirably substantially zero.

[0052] According to a fifth aspect of the present invention there are provided optical pulse transmission line element components for incorporation into an existing terrestrial communication line which comprises a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign, the components comprising:

first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a second dispersion slope parameter (S_2), and

second dispersion slope compensating means of a third length (L_3) having a third dispersion parameter (D_3) and a third dispersion slope parameter (S_3),

the first optical waveguide, the first dispersion slope compensating means and the second dispersion slope compensating means being connectable together in optical communication to thereby form a transmission line element,

wherein the path average dispersion slope of the transmission line element is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2 + S_3 L_3$$

and the path average dispersion ($\langle D \rangle$) of the transmission line element, having a total length $L = L_1 + L_2 + L_3$ is given by

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2}$$

[0053] The path average dispersion of the transmission line element is preferably wavelength independent.

[0054] Preferably, $\pm [D_1(S_3 - S_2) + (D_2 - D_3)S_1] \pm (S_3 - S_2)$ is greater than zero, whereby the path average dispersion may be controlled by selection of the length (L_1) of the first optical waveguide. The path average dispersion of the transmission line element is desirably substantially zero.

[0055] The optical pulse transmission line element preferably forms part of a wavelength division multiplexed optical pulse transmission system.

[0056] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton. The optical pulse may alternatively be a chirped return-to-zero signal.

[0057] The first optical waveguide is preferably a first optical fibre. The first optical fibre may be a transmission fibre, such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.

[0058] The first dispersion slope compensating means is preferably a second optical waveguide. The second optical waveguide is desirably a second optical fibre, which may be a compensating fibre such as reverse dispersion fibre or dispersion compensating fibre. The first dispersion slope compensating means may comprise two parts, each part comprising a section of the second optical fibre.

[0059] The second dispersion slope compensating means preferably comprises a third optical waveguide. The third optical waveguide may be a third optical fibre, which may be a compensating fibre, such as dispersion compensating fibre.

[0060] The second dispersion slope compensating means may alternatively or additionally comprise a fourth optical waveguide including an optical grating. The fourth optical waveguide is preferably a fourth optical fibre. The optical grating is preferably an optical fibre grating, such as a fibre Bragg grating.

[0061] The transmission line element components desirably further comprise at least one optical amplifier, connectable in optical communication with one or more of the above mentioned components and the first optical waveguide.

[0062] The existing terrestrial communication line may comprise a plurality of sections of the first optical waveguide.

[0063] The first dispersion slope compensating means is preferably connectable in optical communication to a first section of the first optical waveguide, to thereby form an optical pulse transmission line portion according to the first aspect of the invention.

[0064] The transmission line element components and the existing terrestrial communication line are desirably connectable together in optical communication to thereby form a transmission line element which comprises:

first and second sections of the first optical waveguide, first and second parts of the first dispersion slope compensating means, and first and second optical amplifiers, connected together in optical communication to thereby form a first optical pulse transmission line portion according to the first aspect of the invention, having a symmetric dispersion map;

optically coupled in series to

a second optical pulse transmission line portion according to the first aspect of the invention comprising the second dispersion slope compensating means, a third section of the first optical waveguide, and a third optical amplifier connected together in optical communication.

[0065] The or each optical amplifier is preferably a fibre amplifier, such as an erbium doped fibre amplifier, or a fibre Raman amplifier. The or each optical amplifier may alternatively comprise a semiconductor amplifier device.

[0066] Desirably, the transmission line element components and the existing terrestrial communication line are connectable together in optical communication to thereby form a plurality of first optical pulse transmission line portions according to the first aspect of the invention, each having a symmetric dispersion map.

[0067] The path average dispersion slope of the or each first optical pulse transmission line portion is desirably substantially zero. The path average dispersion of the or each first optical pulse transmission line portion is desirably non zero and of a first sign.

[0068] The path average dispersion slope of the second optical pulse transmission line portion is desirably substantially zero. The path average dispersion of the second optical pulse transmission line portion is desirably non zero and of the opposite sign.

[0069] The path average dispersion of the optical pulse transmission line element is preferably equal to the sum of the path average dispersion of the or each first optical pulse transmission line portion and the path average dispersion of the second optical pulse transmission line portion. The path average dispersion of the transmission line element is

desirably substantially zero.

[0070] According to a sixth aspect of the invention there is provided an optical pulse transmission line having dispersion compensation and dispersion slope compensation, the transmission line comprising a plurality of transmission line elements according to any of paragraphs 32 to 49 above connected together in optical communication in series.

[0071] The optical pulse transmission line is preferably for inclusion in a wavelength division multiplexed optical pulse transmission system.

[0072] The optical pulse is desirably a return-to-zero optical pulse. The optical pulse is desirably an optical soliton. The optical pulse may alternatively be a chirped return-to-zero signal.

[0073] According to a further aspect of the present invention there is provided a method of manufacturing a pair of optical waveguides for inclusion in an optical pulse transmission line portion according to the first aspect of the present invention, the method including the steps of:

selecting the desired average dispersion ($\langle D \rangle$) of the transmission line portion; and
then selecting

the dispersion parameter (D_1) of the first waveguide of the pair,
the dispersion slope parameter (S_1) of the first waveguide,
the dispersion parameter (D_2) of the second waveguide of the pair, and
the dispersion slope parameter (S_2) of the second waveguide,

such that the following relationship is satisfied

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

[0074] Preferably, each optical waveguide comprises an optical fibre. Each optical waveguide may alternatively comprise a semiconductor waveguide.

[0075] The average dispersion of the transmission line portion may be anomalous, zero or normal. The average dispersion is preferably small, typically less than 1 picosecond/nanometer/kilometer.

[0076] Specific embodiments of the invention will now be described in detail, by way of example only, with reference to the accompanying drawings, in which:

Fig. 1 is a diagrammatic representation of an optical pulse transmission line portion according to a first aspect of the invention;

Fig. 2 is a diagrammatic representation of an alternative optical pulse transmission line portion according to the first aspect of the invention;

Fig. 3 is a diagrammatic representation of a further alternative optical pulse transmission line portion according to the first aspect of the invention;

Fig. 4 is a diagrammatic representation of a further alternative optical pulse transmission line portion according to the first aspect of the invention;

Fig. 5 is a diagrammatic representation of optical pulse transmission line portion components according to a second aspect of the invention;

Fig. 6 is a diagrammatic representation of alternative optical pulse transmission line portion components according to the second aspect of the invention;

Fig. 7 is a diagrammatic representation of an optical pulse transmission line having dispersion slope compensation according to a third aspect of the invention;

Fig. 8 is a diagrammatic representation of an optical pulse transmission line element according to a fourth aspect of the invention;

Fig. 9 is a diagrammatic representation of an alternative optical pulse transmission line element according to the

fourth aspect of the invention;

Fig. 10 is a diagrammatic representation of a further alternative optical pulse transmission line element according to the fourth aspect of the invention;

Fig. 11 is a diagrammatic representation of a further alternative optical pulse transmission line element according to the fourth aspect of the invention;

Fig. 12 is a diagrammatic representation of optical pulse transmission line element components according to a fifth aspect of the invention;

Fig. 13 is a diagrammatic representation of alternative optical pulse transmission line element components according to the fifth aspect of the invention;

Fig. 14 is a diagrammatic representation of further alternative optical pulse transmission line element components according to the fifth aspect of the invention;

Fig. 15 is a diagrammatic representation of further alternative optical pulse transmission line element components according to the fifth aspect of the invention; and

Fig. 16 is a diagrammatic representation of an optical pulse transmission line having dispersion compensation and dispersion slope compensation according to a sixth aspect of the invention.

[0077] Referring to Figs. 1 to 4, the present invention provides an optical pulse transmission line portion 10,20,30,40 having dispersion slope compensation.

[0078] The transmission line portion 10 shown in Fig. 1 comprises a first optical waveguide in the form of a section of standard monomode fibre (SMF) 12 optically coupled to first dispersion slope compensating means in the form of a section of reverse dispersion fibre (RDF) 14. In this example, the transmission line portion 10 further comprises an optical amplifier in the form of an erbium doped fibre amplifier (EDFA) 16 optically coupled to the other end of the RDF 14.

[0079] The SMF 12 has a dispersion parameter (D_1) of 16.2 ps/nm/km at a wavelength of 1550 nm, and a dispersion slope parameter (S_1) of +0.057 ps/nm/nm/km. The RDF 14 has a dispersion (D_2) of -15.36 ps/nm/km at a wavelength of 1550 nm and a dispersion slope (S_2) of -0.053 ps/nm/nm/km.

[0080] The length (L) of the transmission line portion 10 is equal to the sum of the lengths of the SMF 12 (L_1) and the RDF 14 (L_2), in other words

$$L = L_1 + L_2 \quad \text{Equation 1}$$

[0081] The path average dispersion slope of the transmission line portion 10 is required to be substantially zero, and is given by the equation

$$S_1 L_1 + S_2 L_2 = 0 \quad \text{Equation 2}$$

[0082] The path average dispersion of the transmission line portion 10 is generally non-zero, and is given by

$$\langle D \rangle = \frac{D_1 L_1 + D_2 L_2}{L} \quad \text{Equation 3}$$

[0083] The path average dispersion of the transmission line portion may be determined in terms of the dispersion parameter and dispersion slope parameter of the first optical waveguide, being the SMF 12, and the first dispersion slope compensating means, namely the RDF 14, as follows:

[0084] The length (L_2) of the RDF 14 can be expressed through the total length (L) of the transmission line portion 10 and the length (L_1) of the SMF 12, by rearranging equation 1, as follows

$$L_2 = L - L_1$$

Equation 1a

[0085] This equation may be used to replace L_2 in equation 2, and equation 2 then re-arranged to obtain an expression for the length, L_1 , of the SMF 12, as follows

$$L_1 = \frac{S_2 L}{S_2 - S_1}$$

Equation 4

[0086] We then replace the term L_2 in equation 3 with equation 1a, to give the following

$$\langle D \rangle = \frac{D_1 L_1 + D_2 (L - L_1)}{L}$$

Equation 3a

and then replace each term L_1 in equation 3a with equation 4, as follows

$$\langle D \rangle = D_1 \frac{S_2}{S_2 - S_1} + D_2 \left(1 - \frac{S_2}{S_2 - S_1} \right)$$

Equation 3b

which may then be re-arranged to give an expression for the path average dispersion in terms of the dispersion parameters D_1 and D_2 and the dispersion slope parameters S_1 and S_2 , as follows

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

Equation 3c

[0087] It can be seen from equation 3c that the average dispersion does not depend on the wavelength of an optical signal propagating along the transmission line portion 10. The average dispersion is therefore the same for all channels in a WDM system.

[0088] By inserting the dispersion parameters and the dispersion slope parameters of the SMF 12 and the RDF 14 into equation 3c we can then obtain the path average dispersion of the transmission line portion 10 as being -0.16 ps/nm/km. By inserting the dispersion slope parameters of the SMF 12 and RDF 14 into equation 4 we can obtain an expression, as follows, for the length (L_1) of the SMF 12, in terms of the total length (L) of the transmission line portion 10, required in order to make the transmission line portion 10 have a path average dispersion slope of substantially zero:

$$L_1 = 0.48L$$

[0089] The transmission line portion 20 shown in Fig. 2 is of similar construction to that shown in Fig. 1, with the following modifications. The same reference numerals are retained for corresponding features.

[0090] In this example, the first dispersion slope compensating means takes the form of a fibre optic grating 22. The structure and the methods of fabricating a fibre optic grating will be well known to the skilled man and will not be gone into in any detail here. The skilled man will also understand that many different fibre optic gratings may be suitable for use, and that they may be fabricated to have a desired dispersion parameter and dispersion slope parameter. One example of a suitable fibre optic grating is a fibre Bragg grating.

[0091] The above equations, and in particular equations 2 and 3c, may be applied to the transmission line portion 20 shown in Fig. 2. The path average dispersion slope of the transmission line portion 20 may then be set to zero, or close to zero. The path average dispersion of the transmission line portion 20 may be calculated by inserting the dispersion and dispersion slope parameters of the SMF 12 and the fibre optic grating 22 into equation 3c, as described above.

[0092] The transmission line portion 30 shown in Fig. 3 comprises, from left to right across the page i.e. in the direction of propagation of an optical pulse, a first optical waveguide in the form of a section of SMF 12, optically coupled to first

dispersion slope compensating means in the form of a first section of dispersion compensating fibre (DCF) 32, optically coupled to a first optical amplifier in the form of an EDFA 16, optically coupled to a second dispersion slope compensating means in the form of a second section of DCF 32, followed by a second optical waveguide in the form of a second section of SMF, optically coupled to a second EDFA 16. The first and second sections of SMF 12 and the first and second sections of DCF 32 are arranged in a symmetric dispersion map configuration.

[0093] The DCF 32 has a dispersion parameter of -83.1 ps/nm/km and a dispersion slope parameter of -0.3 ps/nm²/km. The path average dispersion of the transmission line portion 30 may be calculated by inserting the dispersion parameter and dispersion slope parameter of the SMF 12 and the DCF 32 into equation 3c. This gives the path average dispersion of the transmission line portion 30 as being 0.35 ps/nm/km. The length of the SMF 12 required to obtain dispersion slope compensation across the transmission line portion 30, may be determined in terms of the total length of the transmission line portion 30 by inserting the dispersion slope parameter of the SMF 12 and the DCF 32 into equation 4, to give

$$L_1 = 0.84L$$

[0094] The transmission line portion 40 shown in Fig. 4 is substantially the same as that shown in Fig. 3, but in this example the first and second dispersion slope compensating means take the form of fibre optic gratings 22. The same reference numerals are retained for corresponding features.

[0095] Equations 2, 3c, and 4 may similarly be applied to this transmission line portion 40, to calculate the path average dispersion and L_1 as a function of L .

[0096] A second aspect of the invention provides optical pulse transmission line portion components 50,60, as shown in Figs. 5 and 6. The components 50,60 are for incorporation into an existing terrestrial communication line. This is desirable in order to allow upgrade of existing communication lines. The existing terrestrial communication line comprises a section of the first optical waveguide, which in this example takes the form of SMF 52. SMF is chosen for this example because many existing optical telecommunications lines comprise at least some sections of this type of optical fibre.

[0097] In the example shown in Fig. 5, the components comprise first dispersion slope compensating means in the form of DCF 32 and an optical amplifier in the form of an EDFA 16. The DCF 32 is connectable in optical communication with the existing SMF 52, to form therewith an optical pulse transmission line portion 54 having compensated dispersion slope.

[0098] The completed transmission line portion 54 has a path average dispersion slope of substantially zero, given by equation 2. The path average dispersion of the completed transmission line portion 54 may be calculated using equation 3c.

[0099] The transmission line portion components 60 shown in Fig. 6 comprise first and second dispersion slope compensating means in the form of sections of RDF 14, and first and second optical amplifiers in the form of EDFAs 16. In this example, the existing terrestrial communication line comprises first and second optical waveguides, in the form of sections of SMF 52. The first EDFA 16 is connected to the first and second sections of RDF 14, being provided in between the two sections of RDF 14. These optical components are then connectable, at the free end of each section of RDF, to the first and second sections of SMF 52 respectively to thereby form an optical pulse transmission line portion having a symmetric dispersion map. The second EDFA 16 is connectable to the other end of the second section of SMF 52.

[0100] As above, the path average dispersion slope of the completed transmission line portion 62 is substantially zero. The path average dispersion of the completed transmission line portion 62 may be determined using equation 3c.

[0101] Fig. 7 shows an optical pulse transmission line 70 having dispersion slope compensation. The transmission line 70 comprises a plurality of, in this example three, optical pulse transmission line portions 10 as shown in Fig. 1, connected together in optical communication in series. The same reference numerals are retained for corresponding features.

[0102] The path average dispersion slope of the transmission line 70 is substantially zero, due to each transmission line portion 10 having a path average dispersion slope substantially equal to zero. The path average dispersion of the transmission line 70 is equal to the path average dispersion of a single transmission line portion 10 multiplied by the number of transmission line portions 10 present. The path average dispersion of the transmission line 70 is therefore -0.48 ps/nm/km.

[0103] It will be appreciated by the skilled man that the transmission line 70 can comprise more than three transmission line portions 10. In addition, it will be appreciated that one or more of the transmission line portions 10 may be replaced by one or more transmission line portions 20,30,40 as shown in Figs. 2, 3 and 4.

[0104] Referring now to figures 8 to 11, a further aspect of the present invention provides an optical pulse transmission line element 80, 90, 100, 110 having both dispersion compensation and dispersion slope compensation.

[0105] The transmission line element 80 shown in Fig. 8 comprises a first optical waveguide in the form of a section of SMF 12 optically coupled to first dispersion slope compensating means in the form of a section of RDF 14. Second dispersion compensating means, being a section of DCF 32 in this example, is optically coupled to the other end of the RDF 14. In this example, the transmission line element also includes an optical amplifier in the form of an EDFA 16, being optically coupled to the other end of the DCF 32.

[0106] The length (L) of the transmission line element 80 is equal to the sum of the lengths of the SMF 12 (L_1), the RDF 14 (L_2) and the DCF 32 (L_3), in other words

$$L = L_1 + L_2 + L_3 \quad \text{Equation 5}$$

[0107] The path average dispersion slope of the transmission line element 80 is required to be substantially zero, and is given by the equation

$$S_1 L_1 + S_2 L_2 + S_3 L_3 = 0 \quad \text{Equation 6}$$

[0108] The path average dispersion of the transmission line element 80 is given by

$$\langle D \rangle = \frac{D_1 L_1 + D_2 L_2 + D_3 L_3}{L} \quad \text{Equation 7}$$

[0109] The path average dispersion of the transmission line element 80 may be determined in terms of the dispersion and dispersion slope parameters of the first optical waveguide and the first and second dispersion slope compensating means, in this example the three fibres 12, 14, 32, the length (L) of the transmission line element 80 and the length (L_1) of the first fibre, as follows:

[0110] The length (L_2) of the second fibre, RDF 14 in this example, can be expressed in terms of the total length (L) of the transmission line element 80 and the length (L_1) of the first fibre by firstly rearranging equation 5 to give

$$L_3 = L - L_1 - L_2 \quad \text{Equation 5a}$$

The term L_3 in equation 6 is then replaced by equation 5a, to give

$$S_1 L_1 + S_2 L_2 + S_3 (L - L_1 - L_2) = 0 \quad \text{Equation 6a}$$

which can then be rearranged to give

$$L_2 = \frac{S_1 L_1 + S_3 (L - L_1)}{S_3 - S_2} \quad \text{Equation 8}$$

[0111] Next, the terms L_2 and L_3 in equation 7 are replaced by equations 8 and 5a respectively, to give

$$\langle D \rangle = \frac{D_1 L_1}{L} + \frac{D_2 S_1 L_1 + S_3 (L - L_1)}{L (S_3 - S_2)} + \frac{D_3}{L} (L - L_1 - L_2) \quad \text{Equation 7a}$$

which may then be rearranged to give the final expression for the path averaged dispersion of the transmission line element 80, as

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2} \quad \text{Equation 7b}$$

[0112] It can be seen from equation 7b that under the condition

$$\pm [D_1(S_3 - S_2) + (D_2 - D_3)S_1] \pm (S_3 - S_2) > 0$$

the average dispersion of the transmission line element may be controlled by selecting the length of L_1 . The use of the + or - signs in the above equation is dependent upon the signs of D_1 and D_2 . This allows transmission line elements having substantially zero dispersion and substantially zero dispersion slope to be constructed.

[0113] Such transmission line elements are of great interest in relation to WDM transmission systems. As was the case for the transmission line portion according to the first aspect of the invention, shown in figures 1 to 4, it can be seen from equation 7b that the average dispersion does not depend on the wavelength of an optical signal propagating along the transmission line element 80. The average dispersion will therefore be the same for all channels in a WDM system.

[0114] By inserting the required parameters into equation 7b we can obtain the path average dispersion of the transmission line element 80 as being

$$\langle D \rangle = -0.82 \left(1 - \frac{L_1}{L} \right) + 0.57 \frac{L_1}{L}$$

[0115] The transmission line element 90 shown in Fig. 9 is of similar construction to the one shown in Fig. 8, with the following modifications. The same reference numerals are retained for corresponding features. In this example, the second dispersion slope compensating means comprises a fibre optic grating 22, such as a fibre Bragg grating.

[0116] Equations 7 to 8 above, and particularly equations 7b and 8, may similarly be applied to this transmission line element 90 in order to determine the path average dispersion. In addition, these equations may be applied during the fabrication of the grating 22 in order to determine the required dispersion and dispersion slope parameters of the grating.

[0117] The transmission line element 100 shown in Fig. 10 comprises two transmission line portions 130, 110, according to the first aspect of the invention, optically coupled together in series. The transmission line portion 110 is similar to the transmission line portion 10 of Fig. 1, with the following modifications. The first dispersion slope compensating means comprises a section of DCF 32. The DCF 32 and the SMF 12 are arranged in a precompensating dispersion map configuration, in which the DCF 32 precedes the SMF 12.

[0118] The transmission line portion 130 is similar to the transmission line portion 30 of Fig. 3, with the following modification. The first dispersion slope compensating means comprises two sections of RDF 14.

[0119] In this example, the sections of RDF 14 and of SMF 12 are each of the same length, which we will call L_1 . The sections of DCF 32 and SMF 12 in the other transmission line portion 110 are of different lengths, which we will call L_2 and L_3 respectively.

[0120] The dispersion and dispersion slope parameters of the three fibres are as follows: dispersion RDF (D_{RDF}) = -20 ps/nm/km; dispersion slope RDF (S_{RDF}) = -0.06 ps/nm/nm/km; dispersion DCF (D_{DCF}) = -83.1 ps/nm/km; dispersion slope DCF (S_{DCF}) = -0.3 ps/nm/nm/km; dispersion SMF (D_{SMF}) = 18 ps/nm/km; and dispersion slope SMF (S_{SMF}) = 0.06 ps/nm/nm/km.

[0121] The path average dispersion slope of the first transmission line portion 130 is, applying equation 2,

$$S_{SMF} 2L_1 + S_{RDF} 2L_1 = 0$$

[0122] The accumulated dispersion of the first transmission line portion 130 is

$$D_{SMF} L_1 + D_{RDF} L_1 + D_{RDF} L_1 + D_{SMF} L_1 = -4L_1 \text{ ps/nm}$$

[0123] The path average dispersion slope of the second transmission line portion 110 is

$$S_{DCF} L_2 + S_{SMF} L_3 = 0$$

[0124] The total dispersion of the second transmission line portion 110 is

$$D_{DCF}L_2 + D_{SMF}L_3 = -83.1 \text{ ps/nm/km } (L_2) + 18 \text{ ps/nm/km } (L_3)$$

if we select the length L_3 of the SMF to be equal to five times the length L_2 of the DCF, then the total dispersion is $6.9L_2$ ps/nm.

[0125] The path average dispersion slope of the transmission line element 100 is equal to the sum of the path average dispersion slopes of the first transmission line portion 130 and the second transmission line portion 110. The path average dispersion slope of each portion 110 and 130 is substantially zero, hence the path average dispersion slope of the transmission line element is substantially zero.

[0126] The path average dispersion of the transmission line element 100 is equal to the sum of the dispersions of the first transmission line portion 130 and the second transmission line portion 110, as follows

$$\langle D \rangle = -4L_1 + 6.9L_2$$

[0127] We can then construct the transmission line element 100 to have substantially zero average dispersion by selecting the lengths L_1 and L_2 so that

$$-4L_1 + 6.9L_2 = 0$$

this can be rearranged to give

$$L_2 = \frac{4L_1}{6.9} = 0.58 L_1$$

i.e., for the above detailed fibres, the transmission line element 100 will have both substantially zero average dispersion and substantially zero average dispersion slope when the length of the DCF 32 (L_2) is equal to 0.58 times the length (L_1) of the fibres in the first transmission line portion 130.

[0128] The transmission line element 120 shown in Fig. 11 is similar to the transmission line element 100 of Fig. 10, with the following modification. In this example, the first transmission line portion 122 comprises a plurality M of transmission line portions 130, as shown in Fig. 10, optically coupled in series. Only the first (A) and last (M) portions 130 are shown for clarity.

[0129] The total dispersion of the first transmission line portion 122 is equal to M times the accumulated dispersion of a single transmission line portion 130, and is therefore $-4M L_1$ ps/nm.

[0130] As above, we can construct the transmission line element 120, using the fibres detailed above, such that the transmission line element 120 will have both substantially zero average dispersion and substantially zero average dispersion slope. This is achieved when length of the DCF 32 (L_2) is equal to $0.58M$ times the length (L_1) of the fibres in the transmission line portions 130A - 130M.

[0131] A further aspect of the invention provides optical pulse transmission line element components 140, 150, 160, 170, as shown in Figs. 12 to 15. The components 140, 150, 160, 170 are for incorporation into an existing terrestrial communication line, in order to upgrade the communication line. The existing communication line comprises one or more sections of a first optical waveguide, in this example SMF 52.

[0132] Referring to Fig. 12, the components comprise first dispersion slope compensating means in the form of RDF 14, optically coupled to second dispersion slope compensating means in the form of DCF 32. In this example the components further comprise an optical amplifier in the form of an EDFA 16, optically coupled to the other end of the DCF 32. The free end of the RDF 14 is connectable in optical communication with one end of the existing SMF 52, to form therewith and optical pulse transmission line element 142 having both dispersion compensation and dispersion slope compensation.

[0133] The completed transmission line element 142 is given substantially zero average dispersion and substantially zero average dispersion slope by appropriately selecting the length of each section of fibre, as discussed above in relation to Figs. 8 to 11.

[0134] The transmission line element components 150 shown in Fig. 13 are similar to those shown in Fig. 12, with the following modification. In this example, the second dispersion slope compensating means comprises an optical grating 22.

[0135] The completed transmission line 152 is constructed to have substantially zero average dispersion and substantially zero average dispersion slope by appropriately selecting the length of the SMF 52, the RDF 14 and the grating

22, and fabricating the grating 22 to have the desired dispersion parameter and dispersion slope parameter.

[0136] The transmission line element components 160 shown in Fig. 14 comprise, components 162 for a first transmission line portion according to the first aspect of the invention, as shown in Fig. 3, and components 164 for a second transmission line portion according to the first aspect of the invention, as shown in Fig. 1.

5 [0137] The first portion components 162 comprise, in this example two sections of RDF 14 and two EDFAs 16. The sections of RDF 14 are optically coupled together via one EDFA 16. The free end of each section of RDF 14 is connectable in optical communication with two existing sections of SMF 52. The other EDFA 16 is connectable in optical communication to the distal end of the second (moving left to right across the page, in the direction of propagation of an optical pulse) section of SMF 52.

10 [0138] The second portion components 164 comprise a section of DCF 32 optically coupled to the second EDFA 16 of the first portion components 162. The free end of the DCF is connectable in optical communication to one end of a third section of existing SMF 52. The second portion components 164 also include a third EDFA 16 which is connectable in optical communication with the other end of the third section of SMF 52.

15 [0139] The components 162, 164 are connectable to the existing sections of SMF 52, as described above, to form therewith an optical pulse transmission line element comprising two transmission line portions according to the first aspect of the invention. The completed transmission line element 166 having dispersion compensation and dispersion slope compensation.

[0140] As discussed above in relation to Fig. 10, the average dispersion of the completed transmission line element is equal to the sum of the dispersion of the two transmission line portions, and can be made to be substantially zero.

20 [0141] The transmission line element components 170 shown in Fig. 15 are similar to those shown in Fig. 14, with the following modification. The components comprise a plurality of sections of RDF 14 and EDFAs 16. The sections of RDF 14 and the EDFAs 16 being connected together and connectable to existing sections of SMF 52, as described above in relation to Fig. 14, in order to form therewith a plurality of transmission line portions 172A to 172M according to the first aspect of the invention.

25 [0142] The plurality of transmission line portions 172A to 172M together form a larger transmission line portion 174. The remaining components, being the DCF 32 and the last EDFA 16, and the final section of SMF 52 are connectable together to form a second transmission line portion 176 according to the first aspect of the invention. The larger transmission line portion 174 is optically coupled to the second transmission line portion 176 so that the portions together form a transmission line element 178 having dispersion compensation and dispersion slope compensation.

30 [0143] Referring to Fig. 16, a further aspect of the invention provides an optical pulse transmission line 180 having both dispersion compensation and dispersion slope compensation. The transmission line 180 comprises a plurality, in this case only two for clarity, of optical pulse transmission line elements 100, as shown in Fig. 3, connected together in optical communication in series. The same reference numerals are retained for corresponding features.

35 [0144] The path average dispersion slope of the transmission line 180 is substantially zero, due to each transmission line element 100 having a path average dispersion slope of substantially zero. The average dispersion of the transmission line 180 is substantially zero, due to each transmission line element 100 having an average dispersion of substantially zero.

40 [0145] The skilled man will appreciate that the transmission line 180 may comprise more than two transmission line elements 100. It will also be appreciated that one or more transmission line portions of the transmission line elements 100 may be replaced with transmission line portions of a different design. In particular, one or more of the first and second dispersion slope compensating means may alternatively or additionally comprise an optical fibre grating.

[0146] The typical current approach to implementing dispersion compensation is to manufacture pairs of optical fibres which simultaneously satisfy the requirement that both the path average dispersion and the path average dispersion slope are zero.

45 [0147] The present invention provides for dispersion slope compensation through the construction of an optical pulse transmission line, portion, or element from existing, commercially available fibres, rather than by using specially manufactured fibres. This is achieved in the case of the transmission line portion by selecting the length of one optical fibre, in terms of the total length of the transmission line portion and the dispersion slope parameters of the fibres to force the path average dispersion slope to be substantially zero. As a result, the path average dispersion of the transmission line portion is generally non-zero.

50 [0148] For the transmission line element this is achieved by selecting the length of one of optical fibre in terms of the total length of the transmission line element, the length of a second optical fibre, and the dispersion and dispersion slope parameters of the fibres from which the transmission line element is constructed. By choosing the appropriate length of L_1 in equation 7b, the average dispersion of the transmission line element can be controlled. A transmission line element can thus be constructed which has both substantially zero average dispersion and substantially zero average dispersion slope. Such a transmission line element is obviously of great interest in relation to WDM systems because it will ensure that each optical channel in a WDM system will experience the same dispersion during propagation along the transmission line element.

[0149] It will be appreciated by the skilled man that the path average dispersion slope will ideally be zero in order to cancel out the differences in dispersion experienced by different wavelength channels in a WDM system. However, the skilled man will also appreciate that it is extremely difficult to achieve a path average dispersion slope of exactly zero in real life situations, a path average dispersion slope of substantially zero being an acceptable workable value.

[0150] Return-to-zero optical pulses can be transmitted along a dispersion-managed optical fibre transmission line having a range of path average dispersion values, including anomalous, zero and normal net dispersion. Optical pulses may therefore be transmitted along the optical pulse transmission line, portion or element according to the invention by adjusting the other carrier signal parameters, which are well known to the skilled man and so will not be gone into in detail here, but would typically include pulse peak optical power, pulse chirp, and dispersion map length, to make use of the resulting path average dispersion.

[0151] As the skilled man will be aware, optical pulse transmission systems employing dispersion-managed return-to-zero optical pulses are typically tolerant against small variations of the average dispersion of the transmission line. Therefore, the transmission line portions and elements according to the invention described above will be tolerant against variations in the average dispersion caused by variations in the dispersion parameters and dispersion slope parameters of the optical fibres from which they are constructed.

[0152] The skilled man will appreciate that the above discussed equations may also be applied during the manufacture of pairs of optical fibres to determine the required dispersion parameters and dispersion slope parameters to construct a transmission line portion having any required (typically small) average dispersion.

[0153] The present invention thus overcomes at least some of the current problems encountered by WDM transmission systems as a result of the dispersion slope parameters of the system fibres. Advantageously, this can be achieved employing existing commercially available optical fibres, rather than by manufacturing a fibre having special dispersion and dispersion slope characteristics. The invention provides a cost-effective optical pulse transmission line design which is advantageous for massive dispersion-managed WDM return-to-zero digital optical signal transmission.

[0154] The invention provides for simultaneous compensation of dispersion and dispersion slope in WDM transmission systems through the design of the transmission line, or parts of the transmission line.

[0155] Various modifications may be made without departing from the scope of the present invention. For example, different types of optical fibre or waveguide may be used in place of the DCF and RDF as dispersion slope compensating means. The SMF may also be replaced by an alternative transmission fibre, such as Lucent 2-wave fibre or Alcatel Terralight fibre. The transmission fibre may alternatively or additionally comprise one or more sections of compensating fibre. The optical fibres or waveguides may have different dispersion parameters and dispersion slope parameters to those described. Some or all of one or more optical waveguides may comprise a semiconductor waveguide rather than optical fibre.

[0156] A different type of optical amplifier may be used in place of the EDFAs described, such as a Raman amplifier. Also, a different type of optical amplifier may be required if semiconductor waveguides are used. One or more optical amplifiers may be semiconductor amplifier devices. Also, a different number of optical amplifiers may be used, and they may be located at different locations along a transmission line portion or element. Alternatively, optical amplifiers may be left out entirely.

[0157] As indicated, one or more dispersion slope compensating means may alternatively or additionally comprise an optical grating, such as a fibre grating. The most well known type of fibre grating is the Bragg grating, but the skilled man will appreciate that other types of fibre grating may alternatively be used, including side-etched gratings. The optical grating may alternatively comprise a semiconductor device, particularly if one or more sections of semiconductor waveguide are used.

[0158] It will be appreciated by the skilled man that a transmission line, element or portion according to the present invention may be of any desired physical length, within the normal constraints of optical pulse transmission systems, which the skilled man will be familiar with and so will not be detailed here.

[0159] Whilst endeavouring in the foregoing specification to draw attention to those features of the invention believed to be of particular importance it should be understood that the Applicant claims protection in respect of any patentable feature or combination of features hereinbefore referred to and/or shown in the drawings whether or not particular emphasis has been placed thereon.

Claims

1. An optical pulse transmission line portion having dispersion slope compensation, the transmission line portion comprising:

a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign,

optically coupled to
 first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2)
 and a dispersion slope parameter (S_2) of the opposite sign,

wherein the path average dispersion slope of the transmission line portion is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2$$

and the path average dispersion ($\langle D \rangle$) of the transmission line portion is generally non zero, and is given by

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

2. An optical pulse transmission line portion according to claim 1 in which the path average dispersion of the transmission line portion is wavelength independent.
3. An optical pulse transmission line portion according to claims 1 or 2 in which the optical pulse transmission line portion is for inclusion in a wavelength division multiplexed optical pulse transmission system.
4. An optical pulse transmission line portion according to any of claims 1 to 3 in which the optical pulse is a return-to-zero optical pulse.
5. An optical pulse transmission line portion according to claim 4 in which the optical pulse is an optical soliton.
6. An optical pulse transmission line portion according to any of claims 1 to 3 in which the optical pulse is a chirped return-to-zero optical signal.
7. An optical pulse transmission line portion according to any preceding claim in which the first optical waveguide and the first dispersion slope compensating means are arranged in a precompensating dispersion map configuration.
8. An optical pulse transmission line portion according to any of claims 1 to 6 in which the first optical waveguide and the first dispersion slope compensating means are arranged in a postcompensating dispersion map configuration.
9. An optical pulse transmission line portion according to claims 7 or 8 in which the transmission line portion further comprises an optical amplifier.
10. An optical pulse transmission line portion according to claim 9 in which the optical amplifier is optically coupled to the dispersion map at one end of the dispersion map.
11. An optical pulse transmission line portion according to claim 9 in which the optical amplifier is optically coupled to the dispersion map at a location along the dispersion map.
12. An optical pulse transmission line portion according to claim 9 in which the transmission line portion further comprises a second optical waveguide of a third length (L_3) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign and a second dispersion slope compensating means of a fourth length (L_4) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign.
13. An optical pulse transmission line portion according to claim 12 in which the first and second optical waveguides and the first and second dispersion slope compensating means are optically coupled together in a symmetric dispersion map configuration.
14. An optical pulse transmission line portion according to claim 13 in which the transmission line portion further comprises a second optical amplifier.
15. An optical pulse transmission line portion according to claim 14 in which one of the first and second optical amplifiers

is provided at an end of the dispersion map and the other of the first and second optical amplifiers is provided towards the middle of the dispersion map.

16. An optical pulse transmission line portion according to any of claims 9 to 15 in which the or each optical amplifier is a fibre amplifier, such as an erbium doped fibre amplifier, or a fibre Raman amplifier.
17. An optical pulse transmission line portion according to any of claims 9 to 15 in which the or each optical amplifier is a semiconductor optical amplifier device.
18. An optical pulse transmission line portion according to any of claims 12 to 17 in which the first and second optical waveguides are a first optical fibre.
19. An optical pulse transmission line portion according to claim 18 in which the first optical fibre is a transmission fibre such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.
20. An optical pulse transmission line portion according to any of claims 12 to 19 in which the first and second dispersion slope compensating means comprise sections of a third optical waveguide.
21. An optical pulse transmission line portion according to claim 20 in which the third optical waveguide is a second optical fibre, which may be a compensating fibre, such as dispersion compensating fibre or reverse dispersion fibre.
22. An optical pulse transmission line portion according to any of claims 12 to 21 in which the first and second dispersion slope compensating means comprise sections of a fourth optical waveguide including an optical grating.
23. An optical pulse transmission line portion according to claim 22 in which the fourth optical waveguide is a third optical fibre, and the optical grating is an optical fibre grating.
24. An optical pulse transmission line portion according to claim 23 in which the optical grating is a fibre Bragg grating.
25. Optical pulse transmission line portion components for incorporation into an existing terrestrial communication line which comprises a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign, the components comprising:

first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign, the first dispersion slope compensating means being connectable in optical communication with the first optical waveguide to form therewith an optical pulse transmission line portion having compensated dispersion slope,

wherein the path average dispersion slope of the transmission line portion is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2$$

and the path average dispersion ($\langle D \rangle$) of the transmission line portion is generally non zero, and is given by

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

26. Optical pulse transmission line portion components according to claim 25 in which the transmission line portion components further comprise a first optical amplifier, being connectable in optical communication with the optical pulse transmission line portion.
27. Optical pulse transmission line portion components according to claim 26 in which the existing terrestrial communication line further comprises a second optical waveguide of a third length (L_3) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign.
28. Optical pulse transmission line portion components according to claim 27 in which the transmission line portion

components further comprise a second dispersion slope compensating means of a fourth length (L_4) having a second dispersion parameter (D_2) and a dispersion slope parameter (S_2) of the opposite sign, and being connectable in optical communication with one or more of the aforementioned components, and the first and second optical waveguides.

29. Optical pulse transmission line portion components according to claim 28 in which the transmission line portion components further comprise a second optical amplifier connectable in optical communication with one or more of the aforementioned components, and the first and second optical waveguides.

30. Optical pulse transmission line portion components according to any of claims 25 to 29 in which the optical pulse transmission line so formed is as defined in any of claims 1 to 24.

31. An optical pulse transmission line having dispersion slope compensation, the optical pulse transmission line comprising a plurality of optical pulse transmission line portions, according to any of claims 1 to 24, connected in optical communication in series.

32. An optical pulse transmission line element having dispersion compensation and dispersion slope compensation, the transmission line element comprising:

a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a first dispersion slope parameter (S_1),
first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a second dispersion slope parameter (S_2), and
second dispersion slope compensating means of a third length (L_3) having a third dispersion parameter (D_3) and a third dispersion slope parameter (S_3),
the first optical waveguide, the first dispersion slope compensating means and the second dispersion slope compensating means being connected together in optical communication to form the transmission line element,

wherein the path average dispersion slope of the transmission line element is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2 + S_3 L_3$$

and the path average dispersion ($\langle D \rangle$) of the transmission line element, having a total length $L = L_1 + L_2 + L_3$ is given by

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2}$$

33. An optical pulse transmission line element according to claim 32 in which the path average dispersion of the transmission line element is wavelength independent.

34. An optical pulse transmission line element according to claims 32 or 33 in which $\pm [D_1 (S_3 - S_2) + (D_2 - D_3) S_1] \pm (S_3 - S_2)$ is greater than zero, whereby the path average dispersion may be controlled by selection of the length (L_1) of the first optical waveguide.

35. An optical pulse transmission line element according to any of claims 32 to 34 in which the path average dispersion of the transmission line element is substantially zero.

36. An optical pulse transmission line element according to any of claims 32 to 34 in which the path average dispersion of the transmission line element is non-zero.

37. An optical pulse transmission line element according to any of claims 32 to 36 in which the optical pulse transmission

line element is for inclusion in a wavelength division multiplexed optical pulse transmission system.

38. An optical pulse transmission line element according to any of claims 32 to 37 in which the optical pulse is a return-to-zero optical pulse.
39. An optical pulse transmission line element according to claim 38 in which the optical pulse is an optical soliton.
40. An optical pulse transmission line element according to any of claims 32 to 37 in which the optical pulse is a chirped return-to-zero signal.
41. An optical pulse transmission line element according to any of claims 32 to 40 in which the first optical waveguide is a first optical fibre.
42. An optical pulse transmission line element according to claim 41 in which the first optical fibre is a transmission fibre, such as standard monomode fibre, Lucent 2-wave fibre or Alcatel Terralight fibre.
43. An optical pulse transmission line element according to any of claims 32 to 42 in which the first dispersion slope compensating means is a second optical waveguide.
44. An optical pulse transmission line element according to claim 43 in which the second optical waveguide is a second optical fibre.
45. An optical pulse transmission line element according to claim 44 in which the second optical fibre is a compensating fibre, such as reverse dispersion fibre or dispersion compensating fibre.
46. An optical pulse transmission line element according to claims 44 or 45 in which the first dispersion slope compensating means comprises two parts, each part comprising a section of the second optical fibre.
47. An optical pulse transmission line element according to any of claims 32 to 46 in which the second dispersion slope compensating means comprises a third optical waveguide.
48. An optical pulse transmission line element according to claim 47 in which the third optical waveguide is a third optical fibre.
49. An optical pulse transmission line element according to claim 48 in which the third optical fibre is a compensating fibre, such as dispersion compensating fibre, or reverse dispersion fibre.
50. An optical pulse transmission line element according to any of claims 32 to 49 in which the second dispersion slope compensating means comprises a fourth optical waveguide including an optical grating.
51. An optical pulse transmission line element according to claim 50 in which the fourth optical waveguide is a fourth optical fibre, and the optical grating is an optical fibre grating, such as a fibre Bragg grating.
52. An optical pulse transmission line element according to any of claims 32 to 51 in which the transmission line element further comprises at least one optical amplifier.
53. An optical pulse transmission line element according to any of claims 32 to 52 in which the transmission line element comprises a plurality of sections of the first optical waveguide.
54. An optical pulse transmission line element according to claim 53 in which a first section of the first optical waveguide and the first dispersion slope compensating means are arranged to form an optical pulse transmission line portion as defined in any of claims 1 to 24.
55. An optical pulse transmission line element according to any of claims 52 to 54 in which the transmission line element comprises:

first and second sections of the first optical waveguide, first and second parts of the first dispersion slope compensating means and first and second optical amplifiers, all being arranged to form a first optical pulse

transmission line portion as defined in any of claims 13 to 24, having a symmetric dispersion map;
optically coupled in series to

a second optical pulse transmission line portion as defined in any of claims 1 to 24 comprising the second dispersion slope compensating means, a third section of the first optical waveguide, and a third optical amplifier.

56. An optical pulse transmission line element according to any of claims 52 to 55 in which the or each optical amplifier is a fibre amplifier, such as an erbium doped fibre amplifier or a fibre Raman amplifier.
57. An optical pulse transmission line element according to any of claims 52 to 55 in which the or each optical amplifier is a semiconductor amplifier device.
58. An optical pulse transmission line element according to any of claims 55 to 57 in which a plurality of first optical pulse transmission line portions as defined in any of claims 13 to 24, having a symmetric dispersion map, are provided, connected together in series in optical communication.
59. An optical pulse transmission line element according to any of claims 55 to 58 in which the path average dispersion slope of the or each first optical pulse transmission line portion is substantially zero.
60. An optical pulse transmission line element according to any of claims 55 to 59 in which the path average dispersion slope of the second optical pulse transmission line portion is substantially zero.
61. An optical pulse transmission line element according to any of claims 55 to 60 in which the path average dispersion of the or each first optical pulse transmission line portion is non zero and of a first sign.
62. An optical pulse transmission line element according to claim 61 in which the path average dispersion of the second optical pulse transmission line portion is non zero and of the opposite sign.
63. An optical pulse transmission line element according to any of claims 55 to 62 in which the path average dispersion of the optical pulse transmission line element is equal to the sum of the path average dispersion of the or each first optical pulse transmission line portion and the path average dispersion of the second optical pulse transmission line portion.
64. An optical pulse transmission line element according to claim 63 in which the path average dispersion of the transmission line element is substantially zero.
65. Optical pulse transmission line element components for incorporation into an existing terrestrial communication line which comprises a first optical waveguide of a first length (L_1) having a first dispersion parameter (D_1) and a dispersion slope parameter (S_1) of a first sign, the components comprising:

first dispersion slope compensating means of a second length (L_2) having a second dispersion parameter (D_2) and a second dispersion slope parameter (S_2), and
second dispersion slope compensating means of a third length (L_3) having a third dispersion parameter (D_3) and a third dispersion slope parameter (S_3),
the first optical waveguide, the first dispersion slope compensating means and the second dispersion slope compensating means being connectable together in optical communication to thereby form a transmission line element,

wherein the path average dispersion slope of the transmission line element is substantially zero and is given by

$$\langle S \rangle = S_1 L_1 + S_2 L_2 + S_3 L_3$$

and the path average dispersion ($\langle D \rangle$) of the transmission line element, having a total length $L = L_1 + L_2 + L_3$ is given by

$$\langle D \rangle = \frac{D_2 S_3 - D_3 S_2}{S_3 - S_2} \left(1 - \frac{L_1}{L} \right) + \frac{L_1}{L} \frac{D_1 (S_3 - S_2) + (D_2 - D_3) S_1}{S_3 - S_2}$$

66. Optical pulse transmission line element components according to claim 65 in which the transmission line element components further comprise at least one optical amplifier connectable in optical communication with one or more of the above mentioned components and the first optical waveguide.

67. Optical pulse transmission line element components according to claim 66 in which the existing terrestrial communication line comprises a plurality of sections of the first optical waveguide.

68. Optical pulse transmission line element components according to claim 67 in which the first dispersion slope compensating means is connectable in optical communication to a first section of the first optical waveguide, to thereby form an optical pulse transmission line portion as defined in any of claims 1 to 24.

69. Optical pulse transmission line element components according to claim 68 in which the transmission line element components and the existing terrestrial communication line are connectable together in optical communication to thereby form a transmission line element which comprises:

first and second sections of the first optical waveguide, first and second parts of the first dispersion slope compensating means, and first and second optical amplifiers, connected together in optical communication to thereby form a first optical pulse transmission line portion as defined in any of claims 13 to 24, having a symmetric dispersion map;
optically coupled in series to

a second optical pulse transmission line portion as defined in any of claims 1 to 24 comprising the second dispersion slope compensating means, a third section of the first optical waveguide, and a third optical amplifier connected together in optical communication.

70. Optical pulse transmission line element components according to claim 69 in which the transmission line element components and the existing terrestrial communication line are connectable together in optical communication to thereby form a plurality of first optical pulse transmission line portions as defined in any of claims 13 to 24, each having a symmetric dispersion map.

71. An optical pulse transmission line having dispersion compensation and dispersion slope compensation, the transmission line comprising a plurality of transmission line elements as defined in any of claims 32 to 64 connected together in optical communication in series.

72. Optical pulse transmission line element components according to any of claims 65 to 71 in which the optical pulse transmission line element so formed is as defined in any of claims 32 to 64.

73. A method of manufacturing a pair of optical waveguides for inclusion in an optical pulse transmission line portion according to the first aspect of the present invention, the method including the steps of:

selecting the desired average dispersion ($\langle D \rangle$) of the transmission line portion; and
then selecting

the dispersion parameter (D_1) of the first waveguide of the pair,
the dispersion slope parameter (S_1) of the first waveguide,
the dispersion parameter (D_2) of the second waveguide of the pair, and
the dispersion slope parameter (S_2) of the second waveguide,

such that the following relationship is satisfied

$$\langle D \rangle = \frac{D_1 S_2 - D_2 S_1}{S_2 - S_1}$$

74. A method according to claim 73 in which each optical waveguide comprises an optical fibre.

75. A method according to claim 73 in which each optical waveguide comprises a semiconductor waveguide.

5 76. A method according to any of claims 73 to 75 in which the average dispersion of the transmission line portion is anomalous, zero or normal.

77. A method according to claim 76 in which the average dispersion is small, typically less than 1 picosecond/nanometer/kilometer.

10 78. Any novel subject matter or combination including novel subject matter disclosed herein, whether or not within the scope of or relating to the same invention as any of the preceding claims.




FIG. 1

FIG. 2




FIG. 3







FIG. 4






FIG. 8





FIG. 9






FIG. 12






FIG. 13






FIG. 16



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 01 30 4727

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	EP 1 087 551 A (KDD CORP.; KDD SUBMARINE CABLE SYSTEMS IN (JP)) 28 March 2001 (2001-03-28) * abstract * * column 2, line 19 - column 3, line 53 * * claims 1,2,12,13; figures 1,2A,2B *	1-11,16, 25,26, 73-78	H04B10/18
X	WO 01 25828 A (CORNING INC) 12 April 2001 (2001-04-12) * abstract * * page 13, line 14 - page 17, line 10 *	1-11,16, 25,26, 73-78	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
			H04B
The present search report has been drawn up for all claims			
Place of search		Date of completion of the search	Examiner
THE HAGUE		24 October 2001	Lazaridis, P
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1803 03 82 (IPOIC01)

ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.

EP 01 30 4727

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

24-10-2001

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
EP 1087551	A	28-03-2001	JP	2001094510 A	06-04-2001
			EP	1087551 A2	28-03-2001
WO 0125828	A	12-04-2001	AU	7826400 A	10-05-2001
			WO	0125828 A2	12-04-2001

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82